



Total Merchant Concepts, Inc.

TIME FOR A CHANGE!

Time Change Instructions

Daylight Savings Time will end on Sunday March 13th, 2011. The following are the time change instructions for the Nurit, Omni, Hypercom, Ingenico, Orion, RDM Synergy, Tranz, Talento, and Eclipse terminals. All times must be in military time. Typically POS Systems will self adjust as do most internet based options!

VERIFONE NURIT - At the idle prompt:

1. Press Menu/Esc
2. Press the Force key to scroll to SYSTEM OPTIONS, press enter
3. At Set Time and Date press enter.
4. Enter the new date then enter the new time.
5. Press enter to review the new Date/Time.
6. Press Menu/Esc back to idle prompt screen.

VERIFONE OMNI 3700 SERIES AND Vx SERIES - At the idle prompt:

1. Press the down arrow key to other set up Select the F key next to other set up
2. Enter Pass Word 1 Alpha Alpha 66831 Press Enter
3. Press down arrow key 2 times to Date/Time F2
4. Enter new date MMDDYYYY
5. Enter New time HHMMSS (Military 24 hours increment)
6. Press the Red X key 2 times back to idle prompt

HYPERCOM TERMINAL - At the idle prompt:

THERE ARE 2 WAYS TO CHANGE THE TIME IN A HYPERCOM TERMINAL.

1. Press the function key, then type in 10 enter and change the time. If this is not programmed, go to step 2.
2. Press initialize
3. Press enter / yes. The terminal will dial out to the server to pick up the time and date change. The screen will finish with Transaction complete and got back to the idle prompt.

INGENICO i5100 ADMIN MENU - At the idle prompt:

(GLOBAL APPLICATION)

This menu is accessed by pressing the "admin" button. The password is 166831.

1. From the main screen press Admin
2. Press 3 for Setup Menu
3. Enter password 166831 and press green enter key
4. Press 1 for Quick Setup
5. Screen will say Quick Setup Clock = with the current date and time on the screen. Choose Button under the edit option on the screen.
6. Enter the date MM/DD/YY format and press green enter key
7. Enter time HH:MM (Military 24 hours increment) and press green enter key
8. Press the Red Cancel key to return to the main screen.

WWW.TotalMerchantConcepts.com

12300 NE 4th Plain Blvd. • Vancouver, WA 98682

Phone: (360)253-5934 • (888)249-9919 • **Fax:** (360)260-7992 • (800)659-5859



Total Merchant Concepts, Inc.

TIME FOR A CHANGE!

INGENICO i7780 ADMIN MENU - At the idle prompt:

(PAYMENTECH APPLICATION)

This menu is accessed by pressing the "admin" button. The password is 166831.

1. DEMO MODE - ENABLE/DISABLE-YES/NO
2. SERVER MENU
 1. ADD SERVER= ENTER SERVER ID
 2. DELETE ID= ALL OR ONE
 3. PRINT ID LIST= (WILL PRINT A LIST OF SERVERS ALREADY LOADED INTO TERMINAL)
3. SETUP MENU
 1. COMMS
 2. DATE AND TIME = YYYYMMDD Press enter Time is Military Time Only

INGENICO AQUA - At the idle prompt:

(GLOBAL APPLICATION)

This menu is accessed by pressing the "admin" button. The password is 166831.

1. From the main screen press Admin
2. Press 3 for Setup Menu
3. Enter password 166831 and press green enter key
4. Press 1 for Quick Setup
5. Screen will say Quick Setup Clock = with the current date and time on the screen. Choose Button under the edit option on the screen.
6. Enter the date MM/DD/YY format and press green enter key
7. Enter time HH:MM (Military 24 hours increment) and press green enter key
8. Press the Red Cancel key to return to the main screen.

ORION IV ACCESS - At the idle prompt

Select Transaction Type

1. Check
2. Credit Card Press [0].

Key-In Password and Press Enter Key in 1234 and press [Enter].

Select Utility

1. IP Diagnostics
2. Configuration Select [2. Configuration]

Configuration

1. Configure Terminal
2. Set Time/Date
3. Update Application
4. Advanced Configuration Select [2. Set Date/Time]

Configuration Date/Time

1. Set Date/Time Manually
2. Sync Date/Time with Server Select [1. Set Date/Time Manually].

Configuration Set Date/Time Manually Time zone (Select the correct time zone).

1. Eastern 2. Central 3. Mountain 4. Pacific

Configuration Set Date/Time Manually Current Date: Example: 11/07/2010 Enter new mm/dd/yyyy 00/00/0000 Key in the date in the MM/DD/YYYY format and press [Enter].

Configuration Set Date/Time Manually

Current Time: Example: 10:03 Enter new time hh:mm 00:00 Key in the time, in the HH:MM format, and press [Enter].

Configuration Set Date/Time Manually Current AM/PM 1. AM 2. PM Select AM or PM

The terminal will reboot

WWW.TotalMerchantConcepts.com

12300 NE 4th Plain Blvd. • Vancouver, WA 98682

Phone: (360)253-5934 • (888)249-9919 • **Fax:** (360)260-7992 • (800)659-5859



Total Merchant Concepts, Inc.

TIME FOR A CHANGE!

RDM SYNERGY ADMIN MENU - At the idle prompt:

1. Press # and 0 at the same time to get to the application menu
2. Press * and then 7 and enter the password (The password is the date in MM/DD/YY format) and press enter
3. Press 4 and enter
4. Enter in the time in HH/MM/SS format (Military 24 hour increment) and press enter
5. Press the clear/cancel key two times to return to the application screen

VERIFONE OMNI 3200 / 3210 - At the idle prompt:

1. Press [enter] and [7] simultaneously
2. System Password? Key in 1 alpha alpha 66831 enter
3. SYSTEM = V.... Press [5]
4. YYMMDD KEY: Date press enter
5. HHMMSS KEY: Enter time and press [enter]
6. Press [CLEAR] to return to idle prompt.

VERIFONE Tranz - At the idle prompt:

This applies to all TRANZ Verifone type terminals.

1. Hold down the * and press 3 simultaneously it will say (DIAGNOSTICS)
2. Press the Alpha Key once it will say (YEAR=1980-2079).
3. NOTE: {on older terminals it may prompt you Enter Day of Week} Enter the number for the coinciding day: Su= 0, M= 1, T= 2, W= 3, Th= 4, F= 5, S= 6.
4. Type in the year (4 DIGITS) press enter
5. Type in the month (2 DIGITS) press enter
6. Type in the day (2 DIGITS) press enter
7. Type in the hours (MILITARY TIME) press enter
8. Type in the minutes (2 DIGITS) press enter
9. Leave seconds at 00 press enter and it will go back to the idle prompt screen.

TALENTO - At the idle prompt:

1. Press the FN key it will prompt you for the manager password.
2. Press 1 enter
3. Press the arrow key once
4. Press Term Set Up
5. Press Clock Set
6. Enter the date press enter
7. Enter the time in MILITARY TIME press enter
8. Press cancel back to idle prompt screen.

ECLIPSE - At the idle prompt:

1. Press OTHER
2. Press SYSTEM
3. Press Date/Time. Change to the appropriate time. AM or PM

If you find that your terminal type was not listed or that you need assistance- you know who to call!!

Total Merchant Concepts

1-888-249-9919

WWW.TotalMerchantConcepts.com

12300 NE 4th Plain Blvd. • Vancouver, WA 98682

Phone: (360)253-5934 • **(888)249-9919** • **Fax:** (360)260-7992 • **(800)659-5859**